

## CLAIMS

01

02

03 I claim:

04

05 1. A Serial Hard Disk Drive Selector mounted permanently within a single  
06  
07 computer system that couples one of a plurality of serial hard disk drives  
08  
09 connected to the computer system through the Serial Hard Disk Drive Selector  
10  
11 to the serial hard disk drive host adapter and a computer system power source  
12  
13 so that the coupled serial hard disk drive occupies a single, logical serial hard  
14  
15 disk drive position and uncouples the other serial hard disk drives of this  
16  
17 plurality of serial hard disk drives during a single computer system use  
18  
19 session, this coupling and uncoupling occurring prior to booting the computer  
20  
21 system and comprising; three component parts, a master control component, a  
22  
23 power control component, and an address/command and control/data control  
24  
25 component; wherein the components are multi-pole, multi-throw switching  
26  
27 elements with predetermined numbers of poles to switch all circuits in each  
28  
29 peripheral bus segment of the computer system they are used in and with  
30  
31 predetermined number of throws to control the selection of the desired serial  
32  
33 hard disk drive attached to the Serial Hard Disk Drive Selector; the three  
34  
35 components are configurable;

36

37 a) the master control component is accessible from the outside of the  
38  
39 computer system's case by the user and synchronously controls the operation  
40  
41 of the power control and the address/command and control/data control  
42  
43 components to close their circuits to the user selected serial hard disk drive to  
44  
45 place the serial hard disk drive in an operational mode and open their circuits

01 to any not-selected serial hard disk drives from the serial hard disk drives  
02  
03 connected to the Serial Hard Disk Drive Selector to place the not-selected  
04  
05 serial hard disk drives in non-operational mode; wherein the master control  
06  
07 component is operated by a switch that has a removable key as a security  
08  
09 feature;  
10  
11 b) the power control component is coupled between the computer system's  
12  
13 electrical supply bus and the power supply terminal of each of the plurality  
14  
15 of the serial hard disk drives; and closes the circuit from the computer  
16  
17 system's power supply to the user selected serial hard disk drive and opens  
18  
19 the circuits to any not-selected serial hard disk drives from the plurality of  
20  
21 the serial hard disk drives connected to the Serial Hard Disk Drive Selector;  
22  
23 c) the address/command/data control component is coupled between the  
24  
25 computer system's serial hard disk drive host adapter and the plurality of  
26  
27 the serial hard disk drives and closes the address/command/data carrying  
28  
29 circuits between the host adapter and the user selected serial hard disk drive  
30  
31 and opens the address/command/data carrying circuits between the host  
32  
33 adapter to the not-selected serial hard disk drives connected to the Serial  
34  
35 Hard Disk Drive Selector.  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45